

Linx-Rx

Short Range Wireless Link



The **Linx-Rx** and **Linx-Fob5** or **Linx-Tx8** form an eight channel short range wireless link. The 1/4 J6 output from the **Linx-Rx** can be used directly to run small relays and solenoids, or fed into any of Gilderfluke's relay modules to control higher current/voltage loads. Most commonly, the output of the **Linx-Rx** is used to start a sound or show playing on a Gilderfluke audio repeater or show controller.

Features of the Linx-Rx include:


- 433 MHz band short range wireless reception from pocket-sized transmitters
- Up to eight outputs can be used to control relays directly, or plug into the 1/4 J6 input of a **v-HD-to-1/4J6**, **Br-Brain4** or **Sd-50**. Can be used to trigger any other Gilderfluke equipment through their optoisolated inputs.
- Draws power through the 1/4 J6 output.
- Indicator LEDs show data being received.
- Plastic enclosure can be mounted remotely, to optimize radio reception.
- Uniquely addressable to one of millions of addresses using a dipswitch.
- Runs on any voltage from nine to twenty-four vdc.

Features of the Linx-Fob5 include:

- Five button keyfob transmitter.
- FCC Part 15, Canadian, and CE certified.
- Allows access to five of the outputs of the **Linx-Rx**
- 2.37" x 1.37" x 0.47". Smaller in size, with slightly shorter range than the **Linx-Tx8**
- Uniquely addressable to one of millions of addresses using a dipswitch.
- Uses a standard 'watch' battery for power.

Features of the Linx-Tx8 include:

- Eight button pocket-sized transmitter.
- FCC Part 15, Canadian, and CE certified.
- Allows access to all eight of the outputs of the **Linx-Rx**
- 2.81" x 1.62" x 0.60" (+1.37" antenna). Larger in size, with slightly longer range than the **Linx-Fob5**
- Uniquely addressable to one of millions of addresses using a dipswitch.
- Uses a standard 'watch' battery for power.



205 South Flower Street • Burbank, California
800/776-5972 • 818/840-9484 • FAX 818/840-9485 • www.gilderfluke.com